



TECHNICAL SPECIFICATION

Ultrasonics – Measurements of electroacoustical parameters and acoustic output power of spherically curved transducers using the self-reciprocity method

INTERNATIONAL
ELECTROTECHNICAL
COMMISSION

ICS 17.140.50

ISBN 978-2-8322-7107-0

Warning! Make sure that you obtained this publication from an authorized distributor.

CONTENTS

FOREWORD.....	5
INTRODUCTION.....	7
1 Scope.....	8
2 Normative references	8
3 Terms and definitions	8
4 Symbols	13
5 General	14
6 Requirements of the measurement system	15
6.1 Apparatus configuration	15
6.2 Measurement water tank.....	15
6.3 Fixing, positioning and orientation systems	15
6.4 Reflector	15
6.5 Current monitor (probe)	15
6.6 Oscilloscope	16
6.7 Measurement hydrophone.....	16
7 Measurement of the effective half-aperture of the spherically curved transducer.....	16
7.1 Setup.....	16
7.2 Alignment and positioning of the hydrophone in the field.....	16
7.3 Measurements of the beamwidth and the effective half-aperture	16
7.4 Calculations of the focus half-angle and the effective area.....	17
8 Measurements of the electroacoustical parameters and the acoustic output power	17
8.1 Self-reciprocity method for transducer calibration.....	17
8.1.1 Experimental procedures	17
8.1.2 Criterion for checking the linearity of the focused field	17
8.1.3 Criterion for checking the reciprocity of the transducer	18
8.2 Calculations of the transmitting response to current (voltage) and voltage sensitivity.....	18
8.3 Calculations of the transmitting response at geometric focus to current (voltage)	18
8.4 Calculation of the pulse-echo sensitivity level	19
8.5 Measurements of the radiation conductance and the mechanical quality factor Q_m	19
8.5.1 Calculations of the acoustic output power and the radiation conductance	19
8.5.2 Measurement of the frequency response of the radiation conductance	19
8.6 Measurement of the electroacoustic efficiency	19
8.6.1 Calculation of the electric input power	19
8.6.2 Calculation of the electroacoustic efficiency.....	20
8.7 Measurement of the electric impedance (admittance).....	20
9 Measurement uncertainty	20
Annex A (informative) Relation of the average amplitude reflection coefficient on a plane interface of water-stainless steel and the focus half-angle for a normally incident beam of a circular spherically curved transducer [6],[7]	21
Annex B (informative) Diffraction correction coefficient G_{sf} in the free-field self-reciprocity calibration method for circular spherically curved transducers in water neglecting attenuation [7],[8],[9]	25

Annex C (informative) Calculation of the diffraction correction coefficient $G_{sf}(R/\lambda, \beta)$ in the free-field self-reciprocity calibration in a non-attenuating medium for a circular spherically curved transducer [7],[8],[9],[10]	27
Annex D (informative) Speed of sound and attenuation in water.....	30
D.1 General.....	30
D.2 Speed of sound for propagation in water [14].....	30
D.3 Acoustic attenuation coefficient for propagation in water.....	30
Annex E (informative) Principle of reciprocity calibration for spherically curved transducers [7],[8],[9],[16],[17],[18],[19]	32
E.1 Principle of reciprocity calibration for an ideal spherically focused field of a transducer	32
E.2 Principle of reciprocity calibration of a real spherically focused field of a transducer	33
E.3 Self-reciprocity calibration of a spherically curved transducer	33
Annex F (informative) Experimental arrangements	38
F.1 Experimental arrangement for determining the effective radius of a transducer [7],[8],[9],[24].....	38
F.2 Experimental arrangement of the self-reciprocity calibration method for a spherically curved transducer [8],[9],[24],[25].....	38
Annex G (informative) Relationships between the electroacoustical parameters used in this application [24].....	40
G.1 Relationship between the free-field transmitting response to voltage (current) and the voltage sensitivity with the radiation conductance	40
G.2 Relationship between the radiation conductance and the electroacoustic efficiency	41
G.3 Relationship between the transmitting response and voltage and acoustic output power.....	41
G.4 Relationship between the pulse echo sensitivity and the radiation conductance	41
Annex H (informative) Evaluation and expression of uncertainty in the measurements of the radiation conductance	42
H.1 Executive standard	42
H.2 Evaluation of uncertainty in the measurement of the radiation conductance	42
H.2.1 Mathematical expression	42
H.2.2 Type A evaluation of standard uncertainty	42
H.2.3 Type B evaluation of standard uncertainty	43
H.2.4 Evaluation of the combined standard uncertainty for the radiation conductance	45
Annex I (informative) Measurement range for power and pressure and examples of electroacoustical parameters obtained	49
I.1 Measurement range of acoustic pressure and power.....	49
I.1.1 Lower limit of acoustic power.....	49
I.1.2 Upper limit of pressure [27].....	49
I.2 Calibrated example of electroacoustical parameters	50
I.2.1 1 MHz focusing transducer with air backing of diameter 80 mm and focal length 200 mm	50
I.2.2 5 MHz focusing transducer with air backing of diameter 20 mm and focal length 20 mm	51
Bibliography.....	52

Figure A.1 – Relation curve of the amplitude reflection coefficient $r(\theta_i)$ on the interface of water-stainless steel for a plane wave with the incident angle θ_i 23

Figure A.2 – Average amplitude reflection coefficient $r_{av}(\beta)$ on the plane interface of water-stainless steel in the geometric focal plane of a spherically curved transducer plotted against the focus half-angle β 24

Figure C.1 – Geometry of the concave radiating surface A of a spherically curved transducer and its virtual image surface A' for their symmetry of mirror-images about the geometric focal plane $(x,y,0)$ 27

Figure E.1 – Spherical coordinates 34

Figure E.2 – Function $G_a(kasin\theta)$, diffraction pattern $F_0(kasin\theta)$ and $F_0^2(kasin\theta)$ in the geometric focal plane [10] 35

Figure F.1 – Scheme of the measurement apparatus for determining the effective half-aperture of a transducer 38

Figure F.2 – Scheme of free-field self-reciprocity method applied to a spherically curved transducer 39

Figure I.1 – The acoustic power as the function of the excitation voltage squared for a 10 MHz spherically curved transducer with backing of diameter 8 mm and curvature 25 mm 49

Figure I.2 – Results of a 1 MHz focusing transducer with a diameter of 60 mm and focal length of 75 mm measured using the self-reciprocity method 50

Figure I.3 – Frequency responses of G , $|S_{ff}|$, $|M|$, $\eta_{a/e}$ for a 1 MHz spherical transducer of diameter 80 mm and focal length 200 mm 50

Figure I.4 – Frequency responses of G , $|S_{ff}|$, $|M|$, $\eta_{a/e}$ for a 5 MHz spherical transducer of diameter 20 mm and focal length 20 mm 51

Table A.1 – Parameters used in calculation of the average amplitude reflection coefficient 22

Table A.2 – Amplitude reflection coefficient $r(\theta_i)$ on a plane interface of water-stainless steel for plane wave for various incident angles θ_i 22

Table A.3 – Average amplitude reflection coefficient $r_{av}(\beta)$ on plane interface of water-stainless steel in the geometric focal plane of a spherically curved transducer for various focus half-angles β 23

Table B.1 – Diffraction correction coefficients G_{sf} of a circular spherically curved transducer in the self-reciprocity calibration method [7],[8],[9] 25

Table D.1 – Dependence of speed of sound in water on temperature 30

Table D.2 – Dependence of α / f^2 in water on temperature 31

Table E.1 – G_a values dependent on $kasin\theta$ for $\beta \leq 45^\circ$ where $x = kasin\theta$ (according to O'Neil [10]) 36

Table E.2 – The $(R/\lambda)_{min}$ values dependent on β when $\theta_{max} \geq \theta_{G_a}$ and $\beta \leq 45^\circ$ for $G_a = 0,94; 0,95; 0,96; 0,97; 0,98; 0,99$ 37

Table H.1 – Type B evaluation of the standard uncertainties (SU) of input quantities in measurement 44

Table H.2 – Components of the standard uncertainty for the measurement of the radiation conductance using the self-reciprocity method 47

Table H.3 – The measurement results and evaluated data of uncertainty for five transducers 48

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**ULTRASONICS – MEASUREMENTS OF ELECTROACOUSTICAL
PARAMETERS AND ACOUSTIC OUTPUT POWER OF SPHERICALLY
CURVED TRANSDUCERS USING THE SELF-RECIPROCITY METHOD**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as “IEC Publication(s)”). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

IEC TS 62903 has been prepared by IEC technical committee 87: Ultrasonics. It is a Technical Specification.

This second edition cancels and replaces the first edition published in 2018. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) Several quantities are recognized as complex-valued quantities in the definitions and in the main text.
- b) Annex I was added to provide typical measurement ranges and to provide example calibration results.

The text of this Technical Specification is based on the following documents:

Draft	Report on voting
87/825/DTS	87/829/RVDTS

Full information on the voting for its approval can be found in the report on voting indicated in the above table.

The language used for the development of this Technical Specification is English.

In this document, the following print types are used:

- terms defined in Clause 3: **in bold type**.

This document was drafted in accordance with ISO/IEC Directives, Part 2, and developed in accordance with ISO/IEC Directives, Part 1 and ISO/IEC Directives, IEC Supplement, available at www.iec.ch/members_experts/refdocs. The main document types developed by IEC are described in greater detail at www.iec.ch/publications.

The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under webstore.iec.ch in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

INTRODUCTION

An ultrasonic transducer is an important acoustic device that can act as a transmitter or a receiver in the applications of medical ultrasound, non-destructive testing, and ultrasonic materials processing. The performance of a transducer is a decisive factor that governs the device's range of applicability, efficiency and quality control in the manufacturing. The mechanisms, transmitting fields, performances, and measurement methods used for these transducers have been studied over the past few decades. However, the electroacoustical characterization and measurement methods applied for spherically curved transducers have not been defined in standard documents for either terms or protocols.

This document defines the relevant electroacoustical parameters for these devices and establishes the self-reciprocity measurement method for spherically curved concave focusing transducers.

ULTRASONICS – MEASUREMENTS OF ELECTROACOUSTICAL PARAMETERS AND ACOUSTIC OUTPUT POWER OF SPHERICALLY CURVED TRANSDUCERS USING THE SELF-RECIPROCALITY METHOD

1 Scope

This document, which is a Technical Specification,

- a) establishes the free-field convergent spherical wave self-reciprocity method for ultrasonic transducer calibration,
- b) establishes the measurement conditions and experimental procedure required to determine the transducer's electroacoustic parameters and acoustic output power using the self-reciprocity method,
- c) establishes the criteria for checking the reciprocity of these transducers and the linear range of the focused field, and
- d) provides guiding information for the assessment of the overall measurement uncertainties for radiation conductance.

This document is applicable to:

- 1) circular spherically curved concave focusing transducers without a centric hole working in the linear amplitude range,
- 2) measurements in the frequency range 0,5 MHz to 15 MHz, and
- 3) acoustic pressure amplitudes in the focused field within the linear amplitude range.

Characterization and sensitivity calibration of hydrophones using the reciprocity method are not addressed in this document but covered in IEC 62127-2 [1]¹ and IEC 60565-1 [2].

2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60050-801, *International Electrotechnical Vocabulary – Chapter 801: Acoustics and electroacoustics*, available at www.electropedia.org

¹ Numbers in square brackets refer to the Bibliography.

3.1 p_{av} **average acoustic pressure**acoustic pressure averaged over the **effective area** of the transducerNote 1 to entry: **Average acoustic pressure** is expressed in pascals (Pa).**3.2** $r_{av}(\beta)$ **average amplitude reflection coefficient**quotient of the **free-field** echo **average acoustic pressure** $p_{av}(\beta)$ reflected by the reflector on the geometric focal plane over the space area coincident with the **effective area** of the spherically curved transducer of focus half-angle β , if the transducer were removed, to the **reference acoustic pressure** p_0 on the **effective area** of the transducer in a non-attenuation medium with negligible diffraction

$$r_{av}(\beta) = p_{av}(\beta)/p_0 \quad (1)$$

3.3 G_{sf} **diffraction correction coefficient**quotient of the **average acoustic pressure** over the spherical segment surface of the spherically curved transducer's virtual image at a position in the distance of twice **geometric focal length** from the transducer, if an ideal reflecting mirror were located on the geometric focal plane, to the **reference acoustic pressure** of the transducer in the **free-field** of a non-attenuation medium**3.4** A **effective area**

<transducer> area of the radiating surface of a theoretically predicted transducer with specific field distribution characteristics that are approximately the same as those of a real transducer of the same type

Note 1 to entry: For a spherically curved transducer, the theoretically predicted acoustic pressure distribution on the geometric focal plane of a transducer is expected to be approximately the same as that of the real transducer with the same **geometric focal length** when operating at the same frequency.Note 2 to entry: The half-aperture of an **effective area** is also named the effective half-aperture or the effective radius.Note 3 to entry: The **effective area** of a transducer is expressed in units of metre squared (m²).**3.5** $\eta_{a/e}$ **electroacoustic efficiency**

quotient of the acoustic output power to the electric input power

3.6**electroacoustical reciprocity principle****electroacoustical reciprocity theorem**principle that the quotient of the **free-field voltage (current) sensitivity** of a **reciprocal transducer** as a receiver, to the **transmitting response to current (voltage)** of the **reciprocal transducer** as a projector is constantNote 1 to entry: This principle is independent of the construction of the **reciprocal transducer**.

3.7**free-field**

sound field in a homogeneous isotropic medium whose boundaries exert a negligible effect on the sound wave

[SOURCE: IEC 61161:2013, 3.2]

3.8

$\underline{M}(f)$

free-field voltage sensitivity receiving voltage response

<of a spherically curved transducer> quotient of the Fourier transform of the open-circuit output voltage signal $\mathcal{F}(U(t))$ of a spherically curved transducer within the field of a point source at its **geometric focus** to the Fourier transform of the **free-field** acoustic pressure waveform $\mathcal{F}(p(t))$ for a specified frequency f and incidence on the surface of the transducer if the transducer were removed

$$\underline{M}(f) = \frac{\mathcal{F}(U(t))}{\mathcal{F}(p(t))} \quad (2)$$

Note 1 to entry: The **free-field voltage sensitivity** of a spherically curved transducer is a complex-value parameter. The modulus of the **free-field voltage sensitivity** of a spherically curved transducer is expressed in units of volt per pascal (V/Pa). The phase angle is the argument of the sensitivity and represents the phase difference between the electrical transducer output voltage and the incident pressure. The unit of phase is the radian.

3.9**geometric beam boundary**

surface containing straight lines passing through the **geometric focus** and all points around the periphery of the transducer aperture

Note 1 to entry: Applies to ultrasonic transducers of known construction.

[SOURCE: IEC 61828:2020, 3.64]

3.10

F_{geo}

geometric focal length

distance from the **geometric focus** to the position where the beam axis intersects the effective focusing surface

Note 1 to entry: Applies to transducers with known construction.

Note 2 to entry: **Geometric focal length** is expressed in metres (m).

Note 3 to entry: This definition applies only to focusing transducers.

[SOURCE: IEC 61828:2020, 3.66]

3.11**geometric focus**

point for which all of the effective path lengths in a specified longitudinal plane are equal

Note 1 to entry: Equivalently, the spatial point for which the arrival times of all waves from the transducer have the same delay relative to the voltage excitation of the transducer, as viewed in the approximation of geometrical acoustics, neglecting diffraction.

Note 2 to entry: This definition applies only to focusing transducers.

[SOURCE: IEC 61828:2020, 3.67]

3.12 L_{Mpe} **pulse-echo sensitivity level**

twenty times the logarithm to the base 10 of the ratio of the received open-circuit voltage U_1 for the first echo signal of the spherically curved transducer when acting as a receiver to the exciting voltage of the transducer U_T when it is transmitting a tone burst ultrasonic beam in a direction perpendicular to an ideal plane reflector ($r = 1$) at the geometric focal plane for a specified frequency

$$L_{Mpe} = 20 \log_{10} \left(\frac{U_1}{U_T} \right) \text{dB} \quad (3)$$

Note 1 to entry: The logarithmic ratio is expressed in decibels (dB).

3.13 G **radiation conductance**

quotient of the acoustic output power and the squared effective transducer input voltage

Note 1 to entry: It is used to characterize the electrical to acoustical transfer of ultrasonic transducers.

Note 2 to entry: The frequency of the input voltage (or current) should be noted.

Note 3 to entry: **Radiation conductance** is expressed in siemens (S).

[SOURCE: IEC 61161:2013, 3.8, modified – In the definition, "RMS" has been replaced with "effective" and "ratio" has been replaced with "quotient".]

3.14**reciprocal transducer**

linear, passive and reversible electroacoustic transducer such that the coupling coefficients are equal for transduction regardless of whether transduction is electrical to mechanical or vice versa

[SOURCE: IEC 60565-1:2020, 3.7]

3.15 \underline{J} **reciprocity coefficient**

<of a transducer> quotient of the **free-field** voltage sensitivity of a **reciprocal transducer** as a receiver to the **transmitting response to current** of the transducer as a projector, or the quotient of the **free-field current sensitivity** of a transducer as a receiver to the **transmitting response to voltage** of the transducer as a projector

$$\underline{J} = \frac{M}{S_I} \quad (4)$$

Note 1 to entry: The modulus of the **reciprocity coefficient** of a spherically curved transducer, $|\underline{J}| = J_{sf}$, is equal to the quotient of twice the **effective area** of the transducer to the acoustic characteristic impedance of the medium, i.e.

$$J_{sf} = \frac{|M|}{|S_I|} = \frac{2A}{\rho c} \quad (5)$$

where

A is the **effective area** of curved surface of the spherically curved transducer;

ρ is the (mass) density of the medium;

c is the speed of sound in the medium (usually water).

Note 2 to entry: The **reciprocity coefficient** is expressed in units of watt per pascal squared (W/Pa²).

3.16

p_0

reference acoustic pressure

product of the uniform normal particle velocity on the spherically curved surface of the transducer and the characteristic impedance of the medium

Note 1 to entry: **Reference acoustic pressure** is expressed in pascals (Pa).

3.17

reversible transducer

transducer capable of acting as a projector as well as a receiver

[SOURCE: IEC 60565-1:2020, 3.8, modified – In the definition, "hydrophone" has been replaced with "receiver".]

3.18

self-reciprocity method

transducer calibration method based on the reciprocity principle that uses the received echo signal from the plane reflector that is set perpendicular to the incident beam axis of the transducer

3.19

$\underline{S}_I(f)$

transmitting response to current

transmitting current response

<of a transducer> quotient of the Fourier transform of the **reference acoustic pressure** $\mathcal{F}(p_0(t))$ on the radiating surface of a transducer in the **free field** in the absence of interference effects to the Fourier transform of the exciting electrical current $\mathcal{F}(I(t))$ through the electrical terminals of the transducer for a specified frequency f

$$\underline{S}_I(f) = \frac{\mathcal{F}(p_0(t))}{\mathcal{F}(I(t))} \quad (6)$$

Note 1 to entry: The **transmitting response to current** of a transducer is a complex-valued parameter. The modulus of the **transmitting response to current** is expressed in units of pascal per ampere, Pa·A⁻¹. The phase angle is the argument of the transmitting response and represents the phase difference between the acoustic pressure at the surface of the transducer and the electric current. The unit of phase angle is the radian.

3.20

$\underline{S}_U(f)$

transmitting response to voltage

transmitting voltage response

<of a transducer> quotient of the Fourier transform of the **reference acoustic pressure** $\mathcal{F}(p_0(t))$ on the radiating surface of a transducer in the **free field** in the absence of interference effects to the Fourier transform of the electrical exciting voltage across the terminals of the **projector** $\mathcal{F}(U_T(t))$, for a specified frequency f

$$\underline{S}_U(f) = \frac{\mathcal{F}(p_0(t))}{\mathcal{F}(U_T(t))} \quad (7)$$

Note 1 to entry: The **transmitting response to voltage** of a transducer is a complex-valued parameter. The modulus of the **transmitting response to voltage** is expressed in units of pascal per volt, Pa·V⁻¹. The phase angle is the argument of the transmitting response and represents the phase difference between the reference acoustic pressure at the surface of the transducer and the exciting electrical voltage. The unit of phase angle is the radian.